

# 6000 Series PAT Testers



Fluke 6200



Fluke 6500

Also available with European mains socket.



## Versatile PAT testing at your fingertips

The Fluke 6200 and 6500 PAT testers verify the electrical safety and operation of portable appliances in accordance with relevant guidelines and regulations. With powerful auto test capabilities and simplified controls they increase the number of tests you can perform per day without compromising results.

### A choice of automatic and manual PAT testers

Both models perform all the tests required for class I and class II appliances. For manual testing and low volume applications, choose the cost-effective 6200 PAT model. If you need a more powerful instrument to test large numbers of appliances, the 6500 is the right choice.

### Fluke simplifies portable appliance testing

- Compact and lightweight... Efficient to work with and easy to carry around- and has extra space in the hard case for accessories.
- One touch simplicity... Pre-set and user-definable test routines are initiated from a single button - to speed up test procedures and save you time on site.
- A better way of working... Rapid data entry via a QWERTY keyboard (or optional Fluke barcode scanner) and fast data transfer from the main memory or the Compact Flash memory card (6500).

## 6200

- Dedicated key for each test for 'one-touch' testing
- Pre-set pass/fail levels to save time
- Large backlit display for easy reading

## 6500

As 6200 but also with:

- Integral QWERTY keyboard for rapid data entry
- Slot for Compact Flash memory card for back-up data storage and transfer to PC
- Pre-set, auto-test sequences for user convenience

## Features

Measurement functions	6200	6500
L N Mains Volts	●	●
Outside Limits Indicators	●	●
Null out facility for earth bond lead	●	●
Protective Earth Resistance PE (200mA)	●	●
Protective Earth Resistance PE (25A)	●	●
Insulation 500V dc	●	●
Protective Earth Conductor Current	●	●
Touch Current	●	●
Substitute Leakage Current	●	●
Appliance Power kVA	●	●
Appliance Load Current	●	●
Seven Segment Custom LCD	●	
Graphical LCD		●
Back Light	●	●
Compact Flash Card receptacle		●
Serial Port - Printing / Downloading	●	●
External printer output	●	●
Front Panel QWERTY Key pad		●
IEC Lead Test	●	●
Auto-testing		●
Pass / Fail Level Programmable Indicators		●
Data Storage		●
Limited Data Storage	●	
Polarity Checks	●	●
Graphical Help Menu On Line		●
Programme Mode		●
Real time clock		●
Front panel results management		●
230V BS1363 Test socket / 230V Mains BS1363 input power plug	●	●

### Included Accessories

Test lead, Test probe, Crocodile clip, Mains cord

### Ordering Information

Fluke 6200 PAT Tester  
Fluke 6500 PAT Tester

Not available in all countries

# 6000 Series PAT Testers



## Separate hard case

The compact Fluke PAT testers are supplied with a hard carrying case that not only offers protection during transit but also includes extra storage space for accessories and other tools. They're extremely light, weighing approximately 3 kg (without case) and have integral carrying handles for extra convenience.



## Special PAT Kit

If you need a complete PAT tester solution, a purpose made kit is available.

Fluke 6500/UK Kit Contains:

- 6500, Mainframe
- EXTL 100, Extension lead test adaptor
- SP Scan 15, Barcode scanner
- Fluke PowerPat Plus
- Pass 560R, Appliance pass labels
- Fail 100S, Appliance fail labels APP 1000, Barcode appliance number labels

(Kit contents may vary per country)

## Display Screens

**Substitute Leakage test I**

Press → to set class II  
Remove test probe then press GO

**Bond test 200mA**

Regularly check the Bond Zero  
Attach test clip to appliance then press GO

Substitute Leakage Current Test

Earth Bond Test (Rpe)

**Insulation test Class II**

Press → to set class I  
Apply test probe then press GO

**Touch current**

Apply test probe and stand well clear then press GO

Insulation Test (Riso)

Touch Current Test

## Specifications

The accuracy specification for the display range is defined as  $\pm$  (%reading + digit counts) at 23 °C  $\pm$  5 °C,  $\leq$  75 % RH. Between 0 °C and 18 °C and between 28 °C and 40 °C, accuracy specifications may degrade by 0.1 x (accuracy specification) per °C. The measurement range meets the service operating errors specified in EN61557-1: 1997, EN61557-2: 1997, EN61557-4: 1997.

Power-on Test	
The test indicates reversed L-N, missing PE, and measures the mains voltage and frequency.	
Display Range	90 V to 264 V
Accuracy at 50 Hz	$\pm$ (2% + 3 counts)
Resolution	0.1 V (1V - model 6200)
Input Impedance	> 1 M $\Omega$ // 2.2 $\mu$ F
Maximum Input Mains Voltage	300 V

Earth Bond Test (Rpe)	
Display Range	0 to 19.99 $\Omega$
Accuracy (after Bond Test zeroing)	$\pm$ (5% + 4 counts)
Resolution	0.01 $\Omega$
Test Current	200 mA ac -0% +40% into 1.99 $\Omega$ 25 A ac $\pm$ 20% into 25 m $\Omega$ at 230 V
Open Circuit Voltage	> 4 V ac, < 24 Vac
Bond Test Zeroing	can subtract up to 1.99 $\Omega$

Insulation Test (Riso)	
Display Range	0 to 299 M $\Omega$
Accuracy	$\pm$ (5% + 2 counts) from 0.1 to 50 M $\Omega$ $\pm$ (10% + 2 counts) from 50 to 299 M $\Omega$
Resolution	0.01 M $\Omega$ (0 to 19.99 M $\Omega$ ) 0.1 M $\Omega$ (20 to 199.9 M $\Omega$ ) 1 M $\Omega$ (200 to 299M $\Omega$ )
Test Voltage	500 V dc -0% +25% at 500 k $\Omega$ load
Test Current	>1 mA at 500 k $\Omega$ load, < 15 mA at 0 $\Omega$
Auto discharge time	< 0.5 s for 1 $\mu$ F
Max. Capacitive Load	operational up to 1 $\mu$ F

Touch Current Test	
Display Range	0 to 1.99 mA ac
Accuracy	$\pm$ (4% + 2 counts)
Resolution	0.01 mA
Internal Resistance (via probe)	2 k $\Omega$
Measuring method	Probe
The appliance under test is energized at mains potential.	

Substitute Leakage Current Test	
Display Range	0 to 19.99 mA ac
Accuracy	$\pm$ (5% + 5 counts)
Resolution	0.01 mA
Test Voltage	35 V ac $\pm$ 20%
Operational Error	10%

Load/ Leakage Test: Load Current	
Display Range	0 to 13 A
Accuracy	$\pm$ (4% + 2 counts)
Resolution	0.1 A
The appliance under test is energized at mains potential.	

Load/Leakage Test: Load Power	
Display Range	0 to 999 VA 1.0 kVA to 3.2 kVA
Accuracy	$\pm$ (5% + 3 counts)
Resolution	1 VA (0 to 999 VA) 0.1 kVA (1.0 kVA to 3.2 kVA)
The appliance under test is energized at mains potential.	

Load/Leakage Test: Leakage Current	
Display Range	0.25 to 19.99 mA
Accuracy	$\pm$ (4% + 4 counts)
Resolution	0.01 mA
The appliance under test is energized at mains potential.	

PELV Test	
Accuracy at 50 Hz	$\pm$ ( 2% + 3 counts)
Overload protection	300 Vrms
Warning threshold	25 Vrms

Size (HxWxD): 200 mm x 275 mm x 100 mm

Weight: 3 kg

Two Years Warranty

## Recommended Accessories

**Fluke PowerPat Plus software**

**SP1000-02**  
Mini printer

**SP-SCAN-15**  
Barcode scanner  
(6500 Fluke only)

**EXTL100-02**  
Extension Test Lead Adaptor

**PASS**  
Appliance 560R Pass Labels

**BDST3 Snap Tags**  
Cable Tie

**BDST4 Snap Tags**  
Clip On