# **AMPROBE®**

**Data Sheet** 



# ECB50A **Circuit Breaker Finder** and AC Cable Tracer

#### Three testers in one

- Identify circuit breaker to an electrical socket
- Trace AC cables in walls
- Sort wires in a bundle

# No hassle warranty

No waiting.

No shipping charges.

Our commitment to high-quality products and customer service is demonstrated by our industry exclusive "No Hassle" warranty. In the unlikely event that an Amprobe Test Tool requires warranty service, any of our local dealers are authorized to replace it, on the spot.

(note: €500 MSLP limit)

- **■** Microprocessor controlled
- **■** Coded transmission allows easy separation of transmitter signal
- Audible and visual indicators
- **■** Low battery indicator
- Cable tracing depth up to 40 cm
- NEMA 5-15 plug



**Included Accessories** Padded carrying case, 9V battery, user's manual











### **ECB50A Circuit Breaker Finder and AC Cable Tracer**

**Data Sheet** 

## **General Specifications**

#### **Transmitter**

Operating temperature range	-10 °C to 40 °C (14 ° to 104 °F ) at max 80 % R.H.
Dimensions	70 x 55 x 86 mm (2.8 x 2.1 x 3.4 in)
Weight	Approximately 65 g (2.3 oz)
Overvoltage category	CAT III 150 V
Pollution degree	2, Protection Class: IP20
Receiver	
Sensitivity setting	Using On/Off control
Low battery indication	7.5 V
Switching fuse/cable	manually using Fuse-Line switch
Operating temperature range	-10 °C to 40 °C (14 ° to 104 °F) at max 80 % R.H.
Dimensions	22 x 162 x 34 mm ( 0.9 x 6.4 x 1.3 in)
Weight	Approximately 100 g (3.5 oz)
Overvoltage category	CAT III 300 V
Pollution degree	2, Protection Class: IP20
Power supply	9 V battery, IEC 6LR61, Alkaline only
Applicable directives	EMC: EN 50081-1 and EN 50082-1, EN61010-1:2001
and standards	

# **Specifications** (Valid for 23 $^{\circ}$ C $\pm$ 5 $^{\circ}$ , for less than 80 $^{\circ}$ relative humidity)

#### Transmitter

Voltage range	100 V to 250 V	
Power consumption	approximately 1 W	
Frequency range	50/60 Hz	
Transmission frequency	Approximately 8 kHz	
Transmitter frequency	Approximately 10 Hz	
Receiver		
Tracing depth for fuse	Approximately 0 to 10 cm (4 in) depending on local conditions	
identification		
Tracing depth for cable location	Approximately 0 to 40 cm (15 in) depending on local conditions	

#### **Amprobe® Test Tools**

website: www.Amprobe.com email: info@amprobe.com Everett, WA 98203 Tel: 877-AMPROBE In den Engematten 14 79286 Glottertal, Germany Tel.: +49 (0) 7684 8009 - 0

www.amprobe.eu info@amprobe.eu

**Beha-Amprobe GmbH** 

©2007 Amprobe Test Tools. All rights reserved. 9/2007 Pub\_ID: 11363-eng